



Sigen Energy Controller

3.0 - 6.0 kW Single Phase

- EMS inside for precise control
 On & off-grid compatibility
- DC ground-fault protection
- Multi-source black start
- DC/AC ratio up to 2
- IP66 system protection rating

Sigen Energy Controller 3.0-6.0 kW Single Phase

| 0 07 | | | 0 | | | | |
|---|--|-----------------|-----------------|------------|--------------|---------------|-------|
| SigenStor EC | 3.0 SP | 3.6 SP | 4.0 SP | 4.6 SP | 5.0 SP | 6.0 SP | Units |
| DC Input (from PV) | | | | J. | | , | |
| Max. PV power | 6000 | 7360 | 8000 | 9200 | 10000 | 12000 | W |
| Max. DC input voltage | 600 | | | | | | V |
| Nominal DC input voltage | 350 | | | | | | V |
| Start-up voltage | 100 | | | | | | |
| MPPT voltage range | 50 ~ 550 | | | | | | V |
| Number of MPP. trackers | 2 | | | | | | |
| Number of PV strings per MPPT | 1 | | | | | | |
| Max. input current per MPPT | 16 | | | | | | А |
| Max. short-circuit current per MPPT | | | 2 | .0 | | | Α |
| AC Output (on-grid) | | | | | | | |
| Nominal output power | 3000 | 3680 | 4000 | 4600 | 5000 | 6000 | W |
| Max. output apparent power | 3300 | 3680 | 4400 | 5000 | 5500 | 6600 | VA |
| Nominal output current | 13.6 | 16.0 | 18.2 | 20.9 | 22.7 | 27.3 | А |
| Max. output current | 15.0 | 16.0 | 20.0 | 22.7 | 25.0 | 30.0 | А |
| Nominal output voltage | 220 / 230 / 240 | | | | | | |
| Nominal grid frequency | 50 / 60 | | | | | | |
| Power factor | 0.8 leading ~ 0.8 lagging | | | | | | |
| Total current harmonic distortion | THDi < 2% | | | | | | |
| Efficiency | | | | | | | |
| Max. efficiency | 98.0% | | | | | | |
| European efficiency | 97.0% | 97.1% | 97.2% | 97.3% | 97.4% | 97.4% | |
| AC Output (backup) | | | | | | | |
| Peak output power (10 seconds) | 4500 | 5520 | 6000 | 6900 | 7500 | 9000 | W |
| Nominal output voltage | | | | 30 / 240 | | (A.T.) T.(T.) | V |
| Nominal output frequency | 50 / 60 | | | | | | |
| Power factor | 0.8 leading ~ 0.8 lagging | | | | | | |
| Total voltage harmonic distortion | THDV < 2% | | | | | | |
| Disruption time of backup switch ¹ | 0 | | | | | | |
| Battery Connection | | | | | | | |
| Battery module models | SigenStor BAT 5.0 / 8.0 | | | | | | |
| Number of modules per controller | 1~6 | | | | | | pcs |
| Battery module voltage range | 300 ~ 600 | | | | | | · V |
| Protection | | | 20, 31.70 - 12 | | | | N. C. |
| Safety protection feature | DC ground fault protection, Arc fault circuit interrupter, DC reverse polarity protection, Insulation monitoring, Residual current monitoring, Type II DC/AC surge protection, Anti-islanding protection, AC overcurrent/overvoltage/short-circuit protection. | | | | | | |
| General Data | | | | | | | |
| Dimensions (W / H / D) | | | 700 / 30 | 00 / 245 | | | mm |
| Weight | 18 | | | | | | kg |
| Storage temperature range | -40 ~ 70 | | | | | | °C |
| Operating temperature range | -30 ~ 60 | | | | | | °C |
| Relative humidity range | 0% ~ 95% | | | | | | |
| Max. operating altitude | 4000 | | | | | | m |
| Cooling | Natural convection | | | | | | |
| System ingress protection rating | IP66 | | | | | | |
| | WLAN / Fast Ethernet / RS485 / Sigen CommMod (4G/3G/2G) | | | | | | |
| Communication | VV | LAN / Fast Etne | ernet / R5485 / | sigen Comm | Mod (4G/3G/2 | G) | |

^{1.} This refers to the load-side disruption time, to achieve this functionality Sigen Energy Gateway needs to be used together with Sigen Energy Controller and Sigen Battery. Test conditions: In the open-circuit state of the power grid, the nominal power of the Sigen Energy Controller is higher than the total power of the home loads.

IEC/EN 62109-1, IEC/EN 62109-2, IEC/EN 62477, IEC/EN 61000-6-1, IEC/EN 61000-6-2

Standard 2

^{2.} For all standards refer to the certificates category in the Sigenergy website.